

# HART™



**DIY Lanterns**  
From: @southernyankeediy

## PROJECT PLAN

**Finished Dimensions:** Varies based on desired size

**Skill Level:** Beginner

## Materials

Item	Qty
1x6	3
1x4	1
2x2	1
1" Nails	
Finishing Nails	
Moss	1
Hot Glue Sticks	1
Wood Glue	1
Finial	1

## Tools Used



Power Drill



Miter Saw



Glue Gun

Also Needed: Nailer, Clamps



**Battery Tip:** A 4.0 Ah battery is recommended to be paired with high amp draw tools for maximum efficiency.

## Lumber Cut List

Board*	Description	Cut to	Qty
2x2	Leg Pieces	12"	4
1X6	Base/Topper	6"	2
1x2	Small Feet Pieces	2"	4
1x4	Accent Piece	3"	1

\* Board dimensions are "nominal." Actual dimensions are smaller due to lumber industry standards. Cuts are actual length.

## Assembly Instructions

### Step 1

Cut (4) 2x2 board to 12" each. These will be the leg pieces

## Step 2

Cut (2) 1x6 boards to 6" each. These will be the bottom & top pieces



---

## Step 3

Start by assembling the legs to the bottom base piece.

---

## Step 4

Apply wood glue, then clamp



---

## Step 5

Screw 1" screws in through the bottom base



## Step 6

Add 1x6 topper to the top using wood glue & finishing nails

---

## Step 7

Next, add 1x4 accent piece to the top center using wood glue & nails.

---

## Step 8

Use scrap 1x2 pieces for small leg pieces. Attach using wood glue & nails.

---

## Step 9

Screw the finial into the accent piece on the top.



## Step 10

Finally it's time to paint the lantern! I went with flat white but feel free to get crazy with the paint colors or even stain.